

MANUFACTURER	COMM. TYPE	MODEL	Link Unit	PARTNUMBERS
IDEC	RS232	Microsmart (FC5A/FC4A)	FC4A-PC1 or FC4A-HPC1	HG9Z-XC183 or FC4A-KC1CA
			Built-in Port (8pin Mini-Din)	FC4A-KC1CA
			FC4A-PC3 or FC4A-HPC3	HG9Z-1C131A
	RS485	OpenNet Controller, Micro3C	FC4A-PC2 or FC4A-HPC2	HG9Z-1C121A
	RS232		Built-in Port (8pin Mini-Din)	HG9Z-XC183
	RS485		Built-in Port (screw terminal)	HG9Z-1C131A
RS485	Micro3	Built-in Port (8pin Mini-Din)	HG9Z-1C121A	
Allen Bradley	RS232	SLC 503/504/505	-	HG9Z-XC100
	RS232	Micrologix Series (1000,1200,1500)	-	HG9Z-XC500
Aromat	RS232	FP0	-	HG9Z-XC300
Automation Direct (Koyo)	RS232	D2-240	-	HG9Z-XC400
Mitsubishi	RS422	FX0,FX0N,FX2N,FX2NC,FX3UC	-	HG9Z-XC245
	RS422	FX1, FX2, FX2C, FX0, FX0N, FX2N, FX2NC, FX3UC	FX-2PIF	HG9Z-XC255
		FX1, FX2, FX2C, FX1S, FX0S	-	
		FX2N, FX1N	FX-20P-CADP + FX2N-422-BD(*) or FX1N-422-BD(*)	
	RS232	Q02CPU	QJ71C24	HG9Z-XC203
	RS232	Q00CPU, Q01CPU, Q02CPU, Q02CPU-A mode	-	HG9Z-XC265
	RS232	A1N,A2N,A3N, A0J2, A0J2H,A2A,A3A,A2U,A3U,A4U	AJ71C24,AJ71C24-S3/-S6/-S8, AJ71UC24, A0J2-C214-S1	HG9Z-XC145
	RS422	A0J2H, A1SJH, A1SH, A2N, A2SH, A2C, A2A, A3A, A2US, A2USH, A2U	Built-in port or FX-2PIF	HG9Z-XC255
	RS232	A1SH, A2US, A2USH-S1	A1SJ71C24-R2, A1SJ71UC24-R2, A1SJ71C24-R4, A1SJ71UC24-R4/R2	HG9Z-XC203
		A2CCPUC24	-	
Omron	RS232	C500,C500F,C1000H,C2000,C2000H	C120-LK201-V1, C500-LK201-V1 C500-LK203	HG9Z-XC155
		C1000HF	C500-LK203	
		C200HS, C120, C120F	C200H-LK201, C120-LK201-	
		C200HE/HG/HX	C200H-LK201-V1	
	RS232	CQM1H,C200HS-CPU21/23/31/33, CPM1, CPM1A, CPM2A	CPM1-CIF01	HG9Z-XC213

**\*\*For other supported PLCs & Cable wiring, please see WindO/I-NV2 Manual (select Host Interface-Connection to a PLC)**